



ENFORCER®

2020

RF Wireless Catalog

Make it Clean. Make it Efficient. Make it Wireless.



1-Channel



2-Channel



4-Channel

One and Two-Channel RF Receivers

- SK-910RBQ** 315MHz, 1 Channel
- SK-910RB2Q** 315MHz, 2 Channel
- SK-910R-4Q** 433.92MHz, 1 Channel
- SK-910RB2-4Q** 433.92MHz, 2 Channel

Features:

- Five programmable relay output modes:
 - 4-Second momentary
 - 1-Second momentary
 - Toggle (ON/OFF)
 - Validity
 - Latch‡
- 11~24 VAC/VDC Operation
- Range: Up to 500ft (150m)*
- Controls garage doors, gates, house lights, alarm panels or other devices via remote
- LED indicates RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode
- Pushbutton programming, no need to cut jumpers‡
- Up to 15 transmitter button codes can be learned



SK-910RBQ / SK-910R-4Q



SK-910RB2Q / SK-910RB2-4Q

5
Output
modes[‡]

11~24
VAC/VDC

LED
Indicators

Up to
500ft*

Specifications:

Model	SK-910RBQ	SK-910RB2Q	SK-910R-4Q	SK-910RB2-4Q
Operating frequency	315MHz		433.92MHz	
Memory capacity	15 transmitter button codes per channel			
Operating voltage	11~24 VAC/VDC			
Operating current	Standby	8mA@12VDC		
	Active	30mA@12VDC per channel		
Relay contact rating	Form C 10A@24VDC per channel			
Connectors	Screw terminals, +, -, with NO/NC/COM per channel			
Dimensions	3 1/8" x 2 9/16" x 1" (80x65x25 mm)		3 1/4" x 2 11/16" x 1 1/16" (83x68x27.5 mm)	

*Operating range will vary greatly depending on the installation and operating environment.

‡Special order item. Contact SECO-LARM for more details.

‡SK-910RBQ, SK-910RB2Q, and SK-910RB2-4Q only

Compatible Transmitters:

Model	315MHz		
	CODEBUMP™	68 Billion Codes	
	Pendant		Handheld
SK-910RBQ	SK-917T1-GBQ	SK-919T1-GBQ	SK-919TP1H-BQ
	SK-917T2-GNQ	SK-919T1-GBUQ	
SK-910RB2Q	SK-917T3-GNQ†	SK-919T2-GNQ	SK-919TP2H-NQ
	SK-917T4-GNQ	SK-919T3-GNQ	SK-919TP4H-NQ
		SK-919T4-GNQ	
433.92MHz Pendant 68 Billion codes			
SK-910R-4Q	SK-939T1-GBUQ		
SK-910R2-4Q	SK-939T2-GNUQ		
	SK-939T3-GNQ†		
	SK-939T4-GNQ†		

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com



Copyright © 2020 SECO-LARM U.S.A., Inc. All rights reserved.

All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners. The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

SECO-LARM® ENFORCER® CRIMEBUSTER® CBA® SLI®

Three and Four-Channel RF Receivers

- SK-910R3Q** 315MHz, 3 Channel
- SK-910R4Q** 315MHz, 4 Channel
- SK-910R4-4Q** 433.92MHz, 4 Channel†‡

Features:

- Four programmable relay output modes:
 - Momentary (1, 2, 3, 4, 5, 10, 30, or 60 seconds)
 - Toggle (ON/OFF)
 - Latch
 - Validity
- 11~24 VAC/VDC Operation
- Range: Up to 500ft (150m)*
- Controls garage doors, gates, house lights, alarm panels or other devices via remote
- LED indicates RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode
- Pushbutton programming, no need to cut jumpers
- Up to 15 transmitter button codes can be learned



SK-910R3Q



SK-910R4Q

4
Output modes

11~24
VAC/VDC

LED
Indicators

Up to
500ft*

Specifications:

Model	SK-910R3Q	SK-910R4Q	SK-910R4-4Q†
Operating frequency	315MHz	433.92MHz	
Memory capacity	15 transmitter button codes per channel		
Operating voltage	11~24 VAC/VDC		
Operating current	Standby	12mA@12VDC	
	Active	50mA@12VDC per channel	
Relay contact rating	Form C 10A@24VDC per channel		
Connectors	Screw terminals, +, -, with NO/NC/COM per channel		
Dimensions	3 1/8" x 2 9/16" x 1" (80x65x25 mm)		

*Operating range will vary greatly depending on the installation and operating environment.
 †Special order item. Contact SECO-LARM for more details.

Compatible Transmitters:

Model	315MHz		
	CODEBUMP™	68 Billion Codes	
	Pendant		Handheld
SK-910R3Q	SK-917T1-GBQ	SK-919T1-GBQ	SK-919TP1H-BQ
	SK-917T2-GNQ	SK-919T2-GNUQ	
SK-910R4Q	SK-917T3-GNQ†	SK-919T3-GNQ	SK-919TP2H-NQ
	SK-917T4-GNQ	SK-919T4-GNQ	
433.92MHz Pendant 68 Billion codes			
SK-910R4-4Q†	SK-939T1-GBUQ		
	SK-939T2-GNUQ		
	SK-939T3-GNQ†		
	SK-939T4-GNQ†		

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com



Miniature One and Two-Channel RF Receivers

SK-910RAQ 3A relay output, 1 Channel

SK-910RAVQ Transistor Group O/P, 1 Channel

SK-910RAV2Q Transistor Group O/P, 2 Channel

Features:

- Four programmable output modes:
 - 4-Second Momentary Output
 - Validity Output
 - Toggle Output
 - 1-Second Momentary Output
- Flexible operating voltage:
 - SK-910RAQ: 11~24VAC/VDC
 - SK-910RAVQ / SK-910RAV2Q: 3~13.8 VDC
- Up to 500ft (150m) range*, 315MHz‡
- Controls garage doors, gates, house lights, alarm panels, or other devices via remote
- Compatible with all 315MHz SECO-LARM transmitters (fixed code and CODEBUMP™)
- LED indicates RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode




SK-910RAQ



SK-910RAV2Q

Specifications:

Model	SK-910RAQ	SK-910RAVQ	SK-910RAV2Q
Operating frequency	315MHz		
Memory capacity	15 transmitter button codes per channel		
Operating voltage	11~24 VAC/VDC	3~13.8 VDC	
Range	Up to 500ft (150m)		
Current draw	Standby	5mA@12VDC	
	LED Flashing	50mA@12VDC	15mA@12VDC
Output mode	Programmable 4-sec. momentary (default), 1-sec. momentary, toggle (ON/OFF), or validity		
Output type	3A Form C relay (NO/NC/COM)	Transistor GND x 1, 5A@12VDC	Transistor GND x 2, 3A@12VDC
Dimensions	3 ³ / ₁₆ "x2 ⁹ / ₁₆ "x3 ¹ / ₄ " (80x65x19 mm)		



Compatible Transmitters:

Model	315MHz		
	CODEBUMP™	68 Billion Codes	
	Pendant		Handheld
SK-910RAQ	SK-917T1-GBQ	SK-919T1-GBQ	SK-919TP1H-BQ
SK-910RAVQ	SK-917T2-GNQ	SK-919T1-GBUQ	SK-919TP2H-NQ
SK-910RAV2Q	SK-917T3-GNQ†	SK-919T2-GNQ	SK-919TP4H-NQ
	SK-917T4-GNQ	SK-919T3-GNQ	
		SK-919T4-GNQ	

*Operating range will vary greatly depending on the installation and operating environment.
 †Special order item. Contact SECO-LARM for more details.
 ‡433.92MHz Miniature RF Receivers also available by special order only. Contact SECO-LARM for more details.

Handheld Slimline RF Transmitters

- SK-919TP1H-BQ** 1-Button, 1-Channel
- SK-919TP2H-NQ** 2-Button, 3-Channel
- SK-919TP4H-NQ** 4-Button, 15-Channel

Features:

- Operates up to 500ft (150m)*
- Over 68 billion (6.8x10¹⁰) possible codes
- LED transmission indicator
- Includes two 3VDC lithium batteries
- Compatible with all SECO-LARM receivers
- Available with SECO-LARM's patented CODEBUMP™ technology. (With CODEBUMP™, Code changes every time transmitter button is pressed.)
- Operating frequency: 315MHz†
- Visor clip and belt clip included. Belt Clip Holster / Wall Mount Switch also available (Model: SK-9HBC)
- Slim-line design: 3 1/2"x2 3/16"x1 1/2" (89x56x12 mm)



SK-919TP1H-BQ



SK-919TP2H-NQ



SK-919TP4H-NQ

Compatible Receivers:

RF Frequency 315MHz	SK-910RBQ SK-910RB2Q SK-910R3Q SK-910R4Q SK-910RAQ SK-910RAVQ SK-910RAV2Q
------------------------	---

Accessories:

SK-9HBC



Belt-clip holster / Wall-mount Bracket
for handheld transmitters

X-930-096



3VDC Lithium battery,
CR2032

*Operating range will vary greatly depending on the installation and operating environment
†433.92MHz Handheld transmitters also available by special order only. Contact SECO-LARM for more details.

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com



Copyright © 2020 SECO-LARM U.S.A., Inc. All rights reserved.
All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners.
The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

SECO-LARM® ENFORCER® CRIMEBUSTER® CBA® SLI®

PI_SK-919TPxH-xxQ_200323.docx

315MHz Pendant RF Transmitters

- SK-919T1-GBQ** 1 Button, 1 Channel
- SK-919T1-GBUQ** 1 Button, 1 Channel, No logo
- SK-919T2-GNQ** 2 Buttons, 3 Channels
- SK-919T3-GNQ** 3 Buttons, 7 Channels
- SK-919T4-GNQ** 4 Buttons, 15 Channels



Features:

- Over 68 billion possible codes
- LED transmission indicator only appears when buttons are pressed
- Operates up to 500ft (150m)*
- RF Anti-scan protection
- FCC, IC, and CE Certified
- 315MHz (433.92MHz available)
- Compatible with all 315MHz SECO-LARM receivers
- Slimline design: 1 1/4"x2 3/16"x5/16" (31.5x55x8 mm)
- CODEBUMP™ codehopping models also available
- Replacement batteries available: X-930-096 (CR2032)
- Patented design

Over
68
Billion
Codes

FC
Certified

LED
Indicator

Up to
500ft*

OEM / ODM Private Label Available:



Compatible Receivers:

RF Frequency	SK-910RBQ
	SK-910RB2Q
	SK-910R3Q
	SK-910R4Q
	SK-910RAQ
	SK-910RAVQ
	SK-910RAV2Q

- Convert your product to wireless control
- All products above are FCC and IC certified to bring your products to market faster (other models available with CE)
- We can provide custom colors, labels, icons, button configurations, and cases, all with your own logo
- Contemporary matching design allows for easy scalability as your product line expands

*Operating range will vary greatly depending on the installation and operating environment

CODEBUMP™ Pendant RF Transmitters

- SK-917T1-GBQ** 1 Button, 1 Channel
- SK-917T2-GNQ** 2 Buttons, 3 Channels
- SK-917T3-GNQ** 3 Buttons, 7 Channels†
- SK-917T4-GNQ** 4 Buttons, 15 Channels



Features:

- CODEBUMP™ anti-codegrabbing technology. Transmitter's code changes on every button pressed (over 18 quintillion possible codes)
- LED transmission indicator only appears when buttons are pressed
- Operates up to 500ft (150m)*
- RF Anti-scan protection
- 315MHz (433.92MHz available)
- Compatible with all 315MHz SECO-LARM receivers
- Slimline design: 1 1/4" x 2 3/16" x 5/16" (31.5x55x8 mm)
- Pre-coded models also available
- Replacement batteries available: X-930-096 (CR2032)
- Patented design

Over
18x10¹⁸
Codes

FC
Certified

LED
Indicator

Up to
500ft*

OEM/ODM Private Label Available:



Compatible Receivers:

RF Frequency	SK-910RBQ
	SK-910RB2Q
	SK-910R3Q
	SK-910R4Q
	SK-910RAQ
	SK-910RAVQ
	SK-910RAV2Q

- Convert your product to wireless control
- All products above are FCC certified to bring your products to market faster (other models available with IC and/or CE)
- We can provide custom colors, labels, icons, button configurations, and cases, all with your own logo
- Contemporary matching design allows for easy scalability as your product line expands

*Operating range will vary greatly depending on the installation and operating environment.

†Special order item. Contact SECO-LARM for more details

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com



433.92MHz Pendant RF Transmitters

- SK-939T1-GBUQ** 1 Button, 1 Channel, No Logo
- SK-939T2-GNUQ** 2 Buttons, 3 Channels, No Logo
- SK-939T3-GNQ** 3 Buttons, 7 Channels†
- SK-939T4-GNQ** 4 Buttons, 15 Channels†



Features:

- Over 68 billion possible codes
- LED transmission indicator only appears when buttons are pressed
- Operates up to 500ft (150m)*
- RF Anti-scan protection
- FCC, IC, and CE Certified
- 433.92MHz (315MHz available)
- Compatible with all 433.92MHz SECO-LARM receivers
- Slimline design: 1 1/4"x2 3/16"x5/16" (31.5x55x8 mm)
- CODEBUMP™ codehopping models also available
- Replacement batteries available: X-930-096 (CR2032)
- Patented design



OEM/ODM Private Label Available:



Compatible Receivers:

RF Frequency	SK-910R-4Q
433.92MHz	SK-910RB2-4Q
	SK-910R4-4Q†

- Convert your product to wireless control
- All products above are FCC, IC, and CE certified to bring your products to market faster
- We can provide custom colors, labels, icons, button configurations, and cases, all with your own logo
- Contemporary matching design allows for easy scalability as your product line expands

* Operating range will vary greatly depending on the installation and operating environment.
 † Special order item. Contact SECO-LARM for more details.