



F01T

Finger Oximeter

Designed for Clinical use, the Sonosat Pulse Oximeter is ideal for the spot checking of blood oxygen saturation levels and pulse rates. Small, simple to use and reliable, the perfect choice for clinicians and in emergency settings.

Features

- Display Mode: 0.96" Dual-color OLED display
- Display content: SpO₂, Pulse rate, Pulse rate waveform, bar graph, battery voltage
- Four different display modes
- Pulse synchronization function
- Pulse Beep function
- Alarm function
- Voltage indication: voltage indicator always appears
- Automatically power off function
- SpO₂ Measuring Range: 0%~100%, (the resolution is 1%) Accuracy: 70%~100%:±2% , Below 70% unspecified
- 10,PR Measuring Range: 18bpm~250bpm, (the resolution is 1bpm) Accuracy: 25bpm~250bpm: ±3bpm, Other range unspecified
- Measurement Performance in Weak Filling Condition: SpO₂ and pulse rate can be shown correctly when pulse-filling ratio is 0.4%. SpO₂ error is ±3%, pulse rate error is ±2 bpm or ±2% (select larger)
- Power Consumption: less than 20mA Voltage: DC 3.5V~4.2V