

Electrisaver

Electronic Timer



The Electrisaver is a simple push button electronic timer that saves energy by remembering to switch off an appliance when you might forget!

Suitable for loads up to 3kW, Electrisaver is a perfect boiler override or extension timer and can also be used on electrical equipment such as panel heaters, immersion heaters, heated towel rails and oil filled radiators.

- Flush or surface mounting
- Wiring is simple with easy access terminals



Electrisaver

Simply press the boost button and walk away, safe in the knowledge that if you forget, Electrisaver won't!

The 3kW rating makes Electrisaver suitable for use with immersion heaters with a range of applications in shops, offices, schools, church halls, student accommodation and all around the home.

- Oil fired radiators
- Towel rails
- Boiler override
- Panel heaters

There are three Electrisaver models which offer preset time periods.

- E15 - 15-60 minutes
- E30 - 30-120 minutes
- E246 - 2-6 hours

Specification

CONTACT RATING	13 Amps 230V AC Suitable for loads up to 3kW
SUPPLY	230V 50Hz
POLLUTION DEGREE	Degree 2
ENCLOSURE PROTECTION	IP30
SHOCK PROTECTION	Class 1
LIVE PARTS	Enclosed
OPERATING TEMPERATURE RANGE	0°C to 35°C
DIMENSIONS	87mm x 87mm x 16mm (Flush mounting) or 51mm (Surface mounting)
MOUNTING	Single gang moulded box (Min. 35mm deep, not supplied)

South Bristol Park, Roman Farm Road, Bristol BS4 1UP
 t: +44 117 978 8700 | f: +44 117 9788701 | e: sales@horstmann.co.uk | www.horstmann.co.uk

Horstmann is a trading name of Secure Controls (UK) Ltd., a wholly owned subsidiary of Secure Holdings PTE Ltd.
 Registered office: Secure House, Moorside Road, Winnall Trading Estate, Winchester, Hampshire, SO23 7RX. Registered in England No. 457553
 © January 2013; Secure Controls (UK) Ltd. All rights reserved. The company reserves the right to alter product specifications without notice.

HORSTMANN